
Module 2~2.5

Gear Couplings

Gear Couplings



oecifications
Normal teeth (crowning)
20°
S45C
Gear teeth induction hardened
50 to 60HRC
Black oxide coating



Catalog Number	Modulo	No. of	Shape	Bore	Hub dia.	Pitch dia.	Outside dia.	Face width	Hub width	Total length	C-shaped	retaining ri	ing groove	Mounting total length	Backlash	Weight
Catalog Number	Module	teeth	Snape	Анв	В	С	D	Е	F	G	K	L	М	N	(mm)	(kg)
GC1-12S	m2	25	T2	12	45	50	54	10	25	35	23	1.95	42.5	73	0.40~0.60	0.43
GC2-20S	m2	40	T2	20	70	80	84	15	40	55	37	2.7	67	115	0.40~0.60	1.66
GC3-20S	m2.5	42	T2	20	90	105	110	20	45	65	42	3.2	86.5	135	0.40~0.60	3.43


[Caution on Product Characteristics] ① A snap ring is included as an accessory.

[Caution on Secondary Operations] ① Due to the gear teeth being induction hardened, no secondary operations can be performed on tooth areas including the bottom land (approx. 2 to 3 mm).

Gear Couplings (Outer Rings)



	Specifications
Gear teeth	Standard full depth
Pressure angle	20°
Material	S45C
Heat treatment	Gear teeth induction hardened
Tooth hardness	50 to 60HRC
Surface treatment	Black oxide coating



T1

Catalog Number	Module	No. of	Shape	Inside dia.	Pitch dia.	Outside dia.	Face width	Backlash	Weight	
Catalog Number	iviodule	teeth	Snape	Α	С	D	Е	(mm)	(kg)	
GC1-I	m2	25		46	50	68	25		0.33	
GC2-I	m2	40	T1	76	80	105	36	0.40~0.60	1.03	
GC3-I	m2.5	42		100	105	145	48		2.96	

[Caution on Secondary Operations] ① Due to the gear teeth being induction hardened, no secondary operations can be performed on tooth areas including the bottom land (approx. 2 to 3 mm).

Series G K K T2

Catalog Number	J
GC1-12SJ BORE	10
GC2-20SJ BORE	13
GC3-20SJ BORE	20



To order J Series products, please specify: Catalog No. + J + BORE.

Bore H7	$\overline{}$			*	The pr	roduct	shapes of J Series items ar				re ider	ntified b	by bacl	kgroun	d colo			
Keyway Js9	J	12	14	15	16	17	18	19	20	22	25	28	30	32	35	40	45	50
Screw size	J	4×1.8	×1.8 5×2.3			6×2.8			8×3.3			10×3.3 12×3.3			3 14×3.8			
Catalog Number	J		M4		M5			M6			M8			M10				
GC1-12SJ BOR	Ε	*T2K	T2K	T2K	T2K	T2K	T2K	T2K	T2K	T2K	T2K							
GC2-20SJ BOR	Ε								*T2K	T2K	T2K	T2K	T2K	T2K	T2K	T2K		
GC3-20SJ BOR	-								*T2K	T2K	T2K	T2K	T2K	T2K	T2K	T2K	T2K	T2K

[Caution on J series] ① As available-on-request products, these require a lead-time for shipping of 2 working days (excludes the day ordered), after placing an order. Because the machining starts immediately, we cannot accept cancellations. Please see Page 38 for more details.

- ② Number of pieces we can process for one order is 1 to 20 units. For larger quantities, please request price and delivery quotes.
- ③ Keyways are made according to JIS B1301 standards, Js9 tolerance. Also note that tooth phase matching is not performed.
- ④ Certain products which would otherwise have a very long tapped hole are counterbored. Please see the Website for more details.
- (5) Areas of products which have been re-worked will not be black oxide coated.
- (6) For products having a tapped hole, a set screw is included.
- 7 Products marked with an * have a bore tolerance of H8.

■ Characteristics of Gear Couplings● There are many ways to couple shafts to transmit power. We

- There are many ways to couple shafts to transmit power. We have developed these standardized gear couplings of our own design. They are easier to connect or disconnect than chain couplings.
- ◆ As the external gear (inner cylinder) is crowned, the shaft angle can be up to 5°.
- Due to the induction hardened gear teeth, these couplings have excellent durability.
- The GCJ units are machined complete with keyways, set screw holes and finished bores and are ready for immediate installation. We also offer minimum bore models for users who want to perform their own secondary operations.

■ Gear Coupling Ordering Method

Gear coupling outer rings and inner hubs can each be purchased individually: however, normal usage requires a set of 1 outer ring and 2 inner hubs.

<E.g.> For 1 set of GC2-20S GC2-I (outer ring) x 1 piece and GC2-20S (inner hub) x 2 piece set.

Strength of Gear Couplings

The allowable torques of the gear couplings are determined in accordance with the shear strength of the keys.

Allowable shear force of keys F (N) is calculated from the following formula.

$$F=b\cdot L\cdot \sigma\cdot \frac{1}{S}$$

Additionally, allowable torques T(N·m) of the inner hubs of the GC gear coupling is calculated using the following formula.

$$T = \frac{F \cdot d}{2000}$$

- b: Key Width mm \rightarrow Keyway width of inner hubs of the GC Gear Coupling
- $L\,$: Key Length $\mathrm{mm} \rightarrow \mathrm{Set}$ at G-2 mm from the total length of the inner hub of the GC Gear Coupling
- σ : Allowable Shear Force of keys \rightarrow Set at 49MPa (5kgf/mm²)
- S: Safety Factor \rightarrow Optionally set
- d: Bore size (mm) \rightarrow Bore size A of the inner hub of the GC Gear Coupling

Caution: Safety Factor (*S*) must be set at a value between 1 to 3, depending on the load types or the coupling displacement.

468